1

TITLE OF THE INVENTION

ELECTRIC POWER VARIATION COMPENSATING DEVICE

BACKGROUND OF THE INVENTION

5   1. FIELD OF THE INVENTION

The present invention relates to an electric power variation compensating device which compensates a variation of an active electric power of wind power (turbine) generators outputted to an electric power

10   system through a control of an electric power converter disposed in parallel with the wind power generators.

2. CONVENTIONAL ART

15   As one of these sorts of conventional devices, Amano et al. "Study on Power Fluctuation Compensation of Wind-Turbine Generators by NAS Battery Systems" (1998 National Convention Record [7] I.E.E. JAPAN, pp 7-310~7-311) discloses a scheme for detection of an active

20   electric power outputted from a wind power generation system and a detection of an active electric power inputted or outputted from an electric power energy storage device through separate current and voltage detectors, and further discloses a scheme for control of an

25   electric power converter constituting the electric power energy storage device in which a detected value of electric power of the wind power generation system

is inputted, respectively, to a high frequency pass filter and a low frequency pass filter to divide the electric power into long period variation components and short period variation components to perform a phase compensation and a gain calculation for the respective components, and the resultant components are added to a charge and discharge command in the control system of the electric power converter.

As has been explained above, since the respective active electric powers of the wind power generation system and the electric power energy storage system are detected separately in the conventional art, there arises a problem that when installing a plurality of wind power generating systems, the number of detecting points thereof increase.

Further, since the active electric power of the wind power generating system is compensated while dividing the same into long period variation components and short period variation components, it is difficult to compensate all of the variation components with the electric power energy storage system.

Still further, if it is difficult to set the gain of the system at unity because of a small capacity of the electric power energy storage system, there arises a problem that all of the electric power variation components can not be compensated.

SUMMARY OF THE INVENTION

An object of the present invention is to provide an electric power variation compensating device which is suitable for suppressing any variation components in an active electric power outputted to an electric power system when an electric power energy storage system is installed in parallel with a plurality of wind power generating systems.

The above object is resolved in the following manner in which the output electric power of the plurality of wind power generators is computed according to a detection value of a composite current and a voltage of an electric power system, and an input or output electric power of an electric power converter is computed according to the voltage of the electric power system and a detected value of current of the electric power converter or a detected value of current of the electric power system. Further, an amount of electric power used for electric power feedback in a control system is obtained by adding either the active electric power or the reactive electric power in the output electric power of the wind power generators, each of which low frequency components are excluded through a low frequency pass filter to either the active electric power or the reactive electric power in the input or output electric power of the electric power converting

4

device, and still further are provided a change-over
switch which makes or interrupts the active electric
power or the reactive electric power in the output
power of the plurality of wind power generators, and

5 another change-over switch which makes or interrupts
low frequency components of the active electric power
or the reactive electric power in the output electric
power of the plurality of wind power generators.

10   BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of an electric power
variation compensating device representing one
embodiment of the present invention;

Fig. 2 is a circuit diagram showing a detailed

15 structural diagram of a control unit according to the
present invention;

Fig. 3 is a diagram illustrating an electric
power variation compensation according to the present
invention;

20   Fig. 4 is another diagram illustrating an
electric power variation compensation according to the
present invention;

Fig. 5 is a diagram illustrating an electric
power variation according to a conventional type

25 device;

Fig. 6 is a block diagram of another embodiment
of the present invention;

Fig. 7 is a ~~block~~ _circuit_ diagram showing a detailed structural diagram of ~~another~~ _the_ control unit in _the_ Fig. 6 embodiment of the present invention;

Fig. 8 is a block diagram of a modification

5　~~example when~~ _in which_ a superconducting magnetic energy storage device is used as the electric power energy storage device of the present invention;

Fig. 9 is a block diagram of another modification ~~example when~~ _in which_ a static var compensating device (SVC) is

10　used as the electric power energy storage device of the present invention; and

Fig. 10 is a block diagram of still another modification ~~example when~~ _in which_ an adjustable speed electric power generating system is used as the electric power

15　energy storage device of the present invention.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Hereinbelow, embodiments of the present invention ~~are~~ _will be_ explained with reference to the drawings.

20　Fig. 1 shows an electric power variation compensating device representing one embodiment of the present invention, in that in Fig. 1, the embodiment is shown which realizes a compound system _formed_ of a wind power generating system 19a and an electric power

25　energy storage use electric power conversion system 7a according to the present invention.

In Fig. 1, a wind power generator 1a is connected

to a coupling ~~use~~ transformer 3a via an inverter/
converter 2a, and the coupling ~~use~~ transformer 3a is
connected to an electric power system 18. The
inverter/converter 2a, _first_ ~~once~~ converts an active electric

5 power Pwa outputted from the wind power generator 1a
into ~~a~~ DC electric power and then inverts the same
into ~~an~~ AC electric power ~~by the inverter~~ to supply
the active electric power to the electric power system
18. Further, another wind power generator 1b is

10 connected to the coupling ~~use~~ transformer 3a and ~~an~~
active electric power Pwb outputted from the wind
power generator 1b is also supplied to the electric
power system 18.

An electric power energy storage device 4a is

15 constituted as an electric power energy storage system
by installing secondary batteries 5a and 5b at DC
circuit portions of inverters 6a and 6b, and the
inverters 6a and 6b are controlled through an inverter
control unit 11a and an active electric power Pc from

20 the electric power energy storage device 4a is
supplied to the electric power system 18 via a
coupling ~~use~~ transformer 3b.

An electric power detector 10a computes,
according to an output current Iw of a current

25 detector 8a and an output voltage Vs of a voltage
detector 9a, electric powers Pw and Qw outputted from
a plurality of wind power generators (in Fig. 1, 1a

and 1b) to the electric power system 18. Further, another electric power detector 10b computes, according to an output current Ic of a current detector 8b and the output voltage Vs of the voltage

5   detector 9a, electric powers Pc and Qc inputted or outputted to and from the electric power energy storage device 4a. Thus ∧obtained , a measure of the active electric powers Pw and Pc and reactive electric powers Qw and Qc ∧are is inputted to the inverter control unit 11a for

10   the electric power energy storage device 4a.

Fig. 2 shows a detailed structure of the inverter control unit 11a for the electric power energy storage device 4a. The ∧composite signals representing the electric powers Pw and Qw of the plurality of wind power generators 1a and 1b are

15   inputted through respective switches A and B. Further, the active electric power Pw is also inputted into a low frequency pass filter 12a and an output PwL of the low frequency pass filter 12a is inputted into a switch C. The switch C outputs the output PwL to a

20   subtracter 14a. The subtracter 14a computes a difference between the output of the switch A and the output of the switch C and outputs the difference to an adder 15a. The adder 15a adds the output active electric power Pc of the electric power energy storage

25   device 4a and the resultant output of the subtracter 14a, and computes an active electric power feed back value pf, and with another subtracter 14b a difference

between an active electric power command p* and the active electric power feed back value pf is computed. Likely, the reactive electric power Qw is inputted via the switch B and another adder 15b adds the reactive

5 electric power Qc inputted into or outputted from the electric power energy storage device 4a and the output from the switch B to compute a reactive electric power feed back value Qf, and with still another subtracter 14c a difference between a reactive electric power

10 command Q* and the reactive electric power feed back value Qf is computed.   The outputs of the subtracters 14b and 14c are inputted into a current controller 13a, and from the current controller 13a gate pulses 16a for the converters 6a and 6b are outputted.

15   When all of the switches A, B and C are in an ON condition, the active electric power feed back value Pf results in an addition of the active electric power Pc and high frequency components of the composite active electric power Pw.   Accordingly, the electric

20 power energy storage device 4a is controlled so that the high frequency components of the active electric power Pw outputted from the wind power generating system 19a are charged/discharged from the batteries 5a and 5b, and thereby, the high frequency components in

25 the active electric power Pw which otherwise flow out into the electric power system 18 are suppressed.

    Now, when assuming that the high frequency

components and the low frequency components of the
active electric power Pw are a̶s̶ PwH and PwL
respectively, since the subtracter 14a subtracts PwL
in Pw (PwH, PwL), the output of the subtracter 14a

5   gives Pw (PwH). The adder 15a adds the output Pw
(PwH) of the subtracter 14a to the output active
electric power Pc of the electric power energy storage
device 4a to obtain the active electric power feed
back value Pf, namely Pc+Pw (PwH). The subtracter 14b

10   computes a deviation ΔpH between the active electric
power command p* and the active electric power feed
back value pf. Based on the computed deviation ΔpH
the current controller 13a outputs the gate pulses 16a
for the converters 6a and 6b. The converters 6a and

15   6b are controlled so that the high frequency
components PwH in the active electric power Pw are
charged/discharged into the batteries 5a and 5b. As a
result, the high frequency components PwH in the
active electric power Pw which possibly flow out into

20   the electric power system 18 are suppressed.
        Fig. 3 shows a relationship between the output
active electric power Pw of the plurality of wind
power generators, the low frequency pass filter output
PwL and an active electric power Psys (=PwL+p*) which

25   the compound system of the wind power generation and
electric power energy storage outputs into the
electric power system 18, when all of the switches A,

B and C are in the ON condition. Since the electric power energy storage device 4a is operated so that the high frequency components in the active electric power Pw from the wind power generating system 19a are

5 eliminated, the active electric power Psys assumes a value obtained by adding the active electric power command value p* for the electric power energy storage device 4a to the low frequency components PwL in the active electric power Pw. In this instance, whether

10 the charging operation or the discharging operation is to be performed by the electric power energy storage device 4a, can be determined by varying the active electric power command value p*. With regard to the reactive electric power, since the switch B is ON, the

15 reactive electric power at the coupling point between the wind power generating system 19a and the electric power energy storage device 4a is controlled so as to meet with the command value Q*.

Fig. 4 shows another relationship between the

20 same, when the switch A is ON and the switch C is OFF. In this instance, since the active electric power Pw of the wind power generating system 19a is added to the detected value Pc of the active electric power of the electric power energy storage device 4a, the

25 electric power energy storage device 4a operates so as to charge or discharge all of the varying components in the active electric power. Accordingly, the

control unit 11a of the electric power energy storage device 4a operates so as to keep the active electric power of the entire compound system of the wind power generation and electric power energy storage at the

5   constant value p*.

Fig. 5 shows still another relationship between the same, when the switches A and C are OFF, which is incidentally an operating example of a conventional type device, wherein the output active electric power

10 Pc of the electric power energy storage device 4a and the active electric power Pw of the wind power generating system 19a are controlled separately, therefore, the active electric power Psys represents the addition of the output active electric power Pc

15 and the active electric power Pw.

As has been explained above, through changing-over of the switches as shown in Figs. 3 and 4, the active electric power of the compound system of the wind power generation and electric power energy

20 storage is caused to follow up the low frequency components in the active electric power of the wind power generating system, thereby to achieve an operating state in which only the high frequency components are compensated, or alternatively an operating state in

25 which all of the active electric power components of the wind power generating system are compensated, can be achieved. In particular, when the electric power

energy storage device 4a does not have a sufficient capacity which can charge all of the electric power of the wind power generating system 19a, an operation which compensates only the high frequency components

5   through changing over switches is effective.

In the present embodiment, since the electric power of not less than two wind power generators is determined according to the composite current and the voltage of the electric power system 18, one set of

10 detection system is sufficient regardless to the number of wind power generators. Further, when adding one or more wind power generators, it is unnecessary to newly add another detection system.

Further, since the detected value of the active

15 electric power of the wind power generating system of which low frequency pass filter output is subtracted is added to the active electric power feed back value of the electric power energy storage device, the high frequency components in the active electric power

20 which otherwise flow out into the electric power system are absorbed by the electric power energy storage device and varying components in the active electric power which will be outputted into the electric power system can be suppressed.

25   Still further, since the switches are provided on the transmission lines of the detected values of electric power of the wind power generators and of the

low frequency pass filter so as to permit change-over, it is possible ~~to cause~~ to follow ~~up~~ the active electric power of the compound system of the wind power generation and electric power energy storage to

5 the low frequency components as well as ~~to cause~~ to perform a compensating operation for all of the active electric power components of the wind power generating system.

Now, other embodiments of the present invention

10 will be explained hereinbelow. Throughout the respective drawings equivalent constituting elements ~~as~~ in the previous embodiment are designated by the same reference numerals and their explanation is omitted.

15 Fig. 6 is another embodiment according to the present invention which realizes a compound system consisting of a wind power generating system and an electric power energy storage use electric power converting system.

The present embodiment is different from the Fig. 1

20 embodiment in the following points, in that in place of the current detector 8b of the electric power energy storage system 7a in Fig. 1 embodiment, the current in the electric power system 18 is detected by a current detector 8d, and the electric powers Psys

25 and Qsys in the electric power system 18 and the detected values Pw and Qw of the electric power of the wind power generating system 19b are fed back to a

control unit 11b constituting an electric power energy
storage system 7b.

Fig. 7 shows a detailed structure of the control
unit 11b of the present embodiment. Since the

5 electric powers Psys and Qsys in the electric power
system 18 are respectively subtracted by the electric
powers Pw and Qw at subtracters 14d and 14e, the
outputs of the subtracters 14d and 14e respectively
give the active electric power Pc and the reactive

10 power Qc which are inputted or outputted to and from
an electric power energy storage device 4b.

With the present embodiment, substantially the
same advantages as ~~has been~~ obtained by ^the^ Fig. 1
embodiment are also obtained.

15 Fig. 8 is a modification ~~example~~ of the present
invention in which a superconducting magnetic energy
storage device 17a which absorbs or discharges ~~an~~
electric power is ^used^ ~~applied for~~ the electric power
energy storage device 4a in Fig. 1 embodiment. In

20 Fig. 8, the superconducting magnetic energy storage
device 17a is connected to the electric power system
18. Further, at the DC circuit portion of an electric
power converter 6e^,^ a superconductor coil 21 is
installed and the superconducting magnetic energy

25 storage device 17a absorbs or discharges ~~an~~ electric
power from and to the electric power system 18
according to a command from a control unit 11c.

The voltage of the electric power system 18 is detected by a voltage detector 9c and currents ~~concerned~~ are detected by current detectors 8e and 8f. Electric power detectors 10d and 10e compute electric

5 powers according to the detected voltage and currents, and~~they~~ output the computed results to a control unit 11c. The control unit 11c outputs gate pulses 16c and controls the superconducting magnetic energy storage device 17a.

10 ~~Other~~ Rather than the ~~above~~ superconducting magnetic energy storage device 17a, a static var compensating device (SVC) 17b as illustrated in Fig. 9 can be used. At the DC circuit portion of an electric power converter 6f in the static var compensating device 17b

15 a capacitor 22a is installed, and the static var compensating device 17b absorbs or discharges ~~an~~ electric power from and to the electric power system 18 according to a command from a control unit 11d.

Further, in place of the superconducting magnetic

20 energy storage device 17a, an adjustable speed electric power generating system can be used. As such adjustable speed electric power generating system, a pumping up electric power generating installation and a fly-wheel type electric power generating system 17c

25 as illustrated in Fig. 10 are exemplified. The fly-wheel type electric power generating system 17c charges a capacitor 22b through an electric power

converter 6h, and another electric power converter 6g uses the electric power of the capacitor 22b for secondary excitation of a generator-motor 23. The rotatable shaft of the generator-motor 23 is coupled with a fly-wheel 24, and further the primary side of the generator-motor 23 is connected to the electric power system 18 via a transformer 3h. The present fly-wheel type electric power generating system 17c absorbs or discharges ~an~ electric power from and to the electric power system 18 according to a command from a control unit 11e.

Hereinabove, it has been explained that when an electric power energy storage system is provided in parallel with a plurality of wind power generating systems, varying components in the active electric power which will be outputted to an electric power system are suppressed. The present invention is likely applicable with regard to a reactive electric power.

As has been explained above, according to the present invention, when an electric power energy storage system is installed in parallel with a plurality of wind power generating systems, through provision for the electric power energy storage system having ~of~ a function which absorbs or discharges high frequency components outputted from the wind power generators, the varying components in the active

electric power outputted into an electric power system
are suppressed and the electric power energy storage
system can be stably operated with regard to charging
and discharging thereby.

5   Further, since the electric power of not less
than two wind power generators is determined according
to the composite current thereof and the voltage of
the electric power system, one ~~set of~~ detection system
is sufficient regardless of ~~to~~ the number of wind power
10 generators, and ~~as well as~~ when adding one or more wind
power generators to the system, it is unnecessary to
newly install another detection ~~system~~ system; therefore, in
the compound system of a wind power generating system
and an electric power energy storage system, the number of
15 detectors can be reduced which achieves a cost reduction
of the system.

Still further, because of the measure in which
the low frequency pass filter output is subtracted
from the detected value of the active electric power
20 of the wind power generating system, the high
frequency components in the active electric power
flowing out into the electric power system are
eliminated with a simple structure and the varying
components in the active electric power which will be
25 outputted into the electric power system can be
suppressed.

Moreover, because of the provision of the

switches in the control system, the mode of electric power detection can be exchanged, the active electric power of the compound system of a wind power generation and an electric power energy storage is

5 caused to follow ~~up~~ the low frequency components of the wind power generating system to thereby compensate only the high frequency components thereof, and an operating condition can be created which performs a compensating operation for all of the active

10 electric power components of the wind power generating system.

Further, with regard to the reactive electric power components, substantially the same compensation can be effected.